



POWERFUL SOLUTIONS IN BATTERY CHARGING

Wa-Charging

Charger: STC				Charging algorithm 02-1				Charg.Factor: 1.15		
Time	5	6	7	8	9	10	11	12	13	14
A	hours	hours	hours	hours	hours	hours	hours	hours	hours	hours
10				50	58	65	73	81	88	96
12				60	70	78	88	97	106	115
15				75	87	98	110	122	132	144
20				100	115	131	146	161	177	192
25				125	144	164	183	202	221	240
30				150	173	196	219	242	265	288
40				200	231	262	292	323	354	384
50				250	289	327	366	404	442	481
60				300	346	392	439	484	530	577
70				350	403	458	512	565	619	673
80				400	462	523	585	646	707	769
100				500	577	654	731	807	884	961
125				625	721	818	914	1009	1105	1201
150				750	866	981	1097	1211	1326	1442
175				875	1010	1145	1279	1412	1547	1682
200				1000	1154	1308	1462	1614	1768	1922
225				1125	1298	1472	1645	1816	1989	2162
250				1250	1443	1635	1828	2018	2210	2403
300				1500	1731	1962	2193	2421	2652	2883
Maximum battery size (Capacity Ah/5h in above table), discharged to 80% will be recharged with chargers market with current shown in the left hand column.										