

Reservdelislista/Spare part list/Ersatzteilliste

Truckladdare/Battery charger/Ladegerät Typ/Type/Typ:

MTM 48/125

In/Input/Eingang: 3x380-400V+N 50Hz

Ut/Output/Ausgang: 48V DC 125A


Recommended Primary Cable: 5x2,5mm²

Secondary cable: N.B No sec.cable

Primärström/Primary current (A/Phase): 16,4 A

Elschema/Circuit diagram/Schaltplan #: E-2510

Kapsling/Cabinet/Gehäuse: F2 not customized



Pos	Benämning/Name/Benennung	Ref	Data
1	Säkring/Fuse/Sicherung	F	3006001 1,25AT 5x20mm
2	Säkring/Fuse/Sicherung	F	3010006 SIBA 160A
3	Kontaktor/Contactor/Kontaktor	K1	3404003 18A 230V 50-60Hz
4	Kontaktor/Contactor/Kontaktor	K2	3404001 9A 230V 50-60Hz
5	Strömbrytare/Switch/Stromschalter	S1	3602001 Standard 16A 2-pole
6	Fläkt/Fan/Ventilator	E	3801001 220-240VAC 120x120 1 pcs out + 1 pcs heat sink
7	Tyristor/Thyristor/Thyristor	Ty	4202003 3 pcs 81RIA40 1/2"
8	Diod/Diode/Diode pos	D	4302001 6 pcs 40HF40
9	Diod/Diode/Diode neg	D	-
10	Motstånd/Resistor/Widerstand	R	4621001 100R 6W CW-5
11	Varistor/Varistor/Varistor	Va1	4635001 1 pcs 250V 20J
12	Varistor/Varistor/Varistor	Va2	4635001 1 pcs 250V 20J
13	Transformator/Transformer/Transformator	T	5254472 3 pcs
14	Drossel/Choke/Drossel	L	5600450 3 pcs
15	Manöver trafo/Aux.transf/	T	- - pcs
16	Extra lindad enhet 1/ Extra	-	- - pcs
17	Moderkort/Main pcb/Haupt l.b	U1	8001146 Kk112806 Main pcb
18	Datorkort/Processor pcb/Computer l.b	U2	8001137 Kk105007 Proc. pcb
19	Optionskort 1 /Optional pcb 1	U3	-
20	Optionskort 2 / Optional pcb 2	U4	-
21	Optionskort 3 / Optional pcb 3	U5	-